

## AquaMark Stock Booster Circuit Breaker Recommendations

Model Number	Horsepower	Voltage	Phase	Maximum Amperage Draw	Recommended Circuit Breaker
AM-LG	1	120	Single	16.6	20
AM-15V	1	120	Single	20	20
AM-25V	1.5	120	Single	20	30
AM-30V	2	240	Single	13.3	20
<b>AM-30V</b>	<b>2</b>	<b>208/240</b>	<b>Three</b>	<b>8.1</b>	<b>20</b>
AM-50V	3	240	Single	17.1	20
<b>AM-50V</b>	<b>3</b>	<b>208/240</b>	<b>Three</b>	<b>10.8</b>	<b>20</b>
AM-60V	3	240	Single	17.1	20
<b>AM-60V</b>	<b>3</b>	<b>208/240</b>	<b>Three</b>	<b>10.8</b>	<b>20</b>
AM-80V-1	3	240	Single	17.1	20
<b>AM-80V-3</b>	<b>5</b>	<b>208/240</b>	<b>Three</b>	<b>18.6</b>	<b>30</b>
<b>AM-100V</b>	<b>5</b>	<b>208/240</b>	<b>Three</b>	<b>18.6</b>	<b>30</b>
<b>AM-150V</b>	<b>7.5</b>	<b>208/240</b>	<b>Three</b>	<b>26</b>	<b>40</b>
<b>AM-80V-3</b>	<b>5</b>	<b>400/480</b>	<b>Three</b>	<b>10.6</b>	<b>20</b>
<b>AM-100V</b>	<b>5</b>	<b>400/480</b>	<b>Three</b>	<b>10.6</b>	<b>20</b>
<b>AM-150V</b>	<b>7.5</b>	<b>400/480</b>	<b>Three</b>	<b>14.2</b>	<b>20</b>

Please call AquaMark at (800) 323-4498 for circuit breaker recommendations for equipment other than specified above.

5/6/2020